






## San Marcos ILAST How to Make Audio Dubs (New Sound Tracks)



*great for language arts, writing, or other curriculum  
depending on the tape you use*

### Equipment needed:

1. 2 VCRs (or VCR and camcorder)
2. CD , cassette player (or other music source with headphone output)
3. microphone
4. cord 1 - RCA male to RCA male
5. cord 2 - RCA male to RCA male note: some VCRs may take a stereo cable, but mono (one connector) will always work using the left channel.
5. cord 3 - mini-male stereo to RCA male
6. TV set (plus connection cable from VCR)

**Team jobs:** Actors (Romeo and Juliet); technical director to push the buttons on the VCRs; sound mixer to start CD player (etc.) and mix sound; director to coordinate everything. Writing in teams is also a job.

### How to Do It

Put the original tape in VCR 1. Put a blank tape in VCR 2. Connect *video out* on VCR 1 to *video in* on VCR 2 with cord 1. **Important!:** Set VCR 2 to *line in*. This will show on the VCR instead of a channel number. If you see a channel number on VCR 2, you need to change it using the remote control or the channel up button. Connect microphone, CD player, etc., to the mixer. Use cable 3 for the CD player (or other sound source) using the headphone jack.

**Play** on VCR 1. **Record** on VCR 2. You will be able to see the tape on the television as you make your new sound track. The SP speed makes the best tapes.

